YEAR WARRANTY





KT-LED54HID-EX39-850-D HID REPLACEMENT LED LAMP

DESCRIPTION

54W HID Replacement LED Lamp | 5000K | >83 CRI | IP64 Rated

LAMP TYPE: HID Replacement LED

BASE TYPE: EX39 (Mogul)

WATTAGE: 54W

COLOR TEMPERATURE: 5000K

METAL HALIDE EQUIVALENT: 250W

COLOR RENDERING INDEX (CRI): >83

WARRANTY: 5 Years

PRODUCT FEATURES

- Replacement for Conventional Metal Halide Lamp
- Non-Dimmable; Do Not Dim
- 50,000+ Hour Lifetime
- Environmentally Friendly: No Mercury Used
- Instant Startup
- UL Listed
- Operating Temperature: -29°C/-20°F to 60°C/140°F
- Up To 100% Rated Power DLC QPL Listed

Includes 4kV Surge Protection

Intrusion Out of the Lamp

OPERATING SPECIFICATIONS

ELECTRICAL CHARACTERISTICS


| Input Voltage | Power Consumption | Power Factor | Input Current |
|---------------|-------------------|--------------|------------------------------|
| 120-277Vac | 54W | >0.9 | 0.47A @ 120V 0.20A @ 277V |
| | | | |

50,000

AI ED LIFE

L70 (Hours)

SPECTRAL DISTRIBUTION



PHOTOMETRIC CHARACTERISTICS

• Integral Driver, Eliminates the Need for External Driver or Ballast;


• IP64 Rated; Integrated Heat Sink Quickly Dissipates Heat and Guides Water

• Active Cooling Technology: When Internal Thermal Sensor Reaches 84°C, Lamp

Power Reduces To 80% Of Max; When Sensor Cools To 65°C Lamp Powers Back

| Color Temperature (CCT) | 5000K | |
|-----------------------------|----------|--|
| Luminous Flux | 7660 lm | |
| Color Rendering Index (CRI) | >83 | |
| Efficacy | 142 Im/W | |
| Visible Light Area | 360° | |

LUX DISTANCE CURVE



Keystone Technologies • 1390 Welsh Road, North Wales, PA 19454 • Phone (800) 464-2680 • Fax (888) 966-0556 • www.keystonelamp.com




RoHS Compliant





KT-LED54HID-EX39-850-D HID REPLACEMENT LED LAMP



E39 MOGUL SOCKET

WIRING DIAGRAM

STEP 1

Disconnect power. Disconnect and remove existing ballast, capacitor, and/or ignitor (where applicable) from fixture.

STEP 2


Rewire for line voltage to the lamp socket.


STEP 3

Install new LED replacement lamp. Ensure lamp is operating properly when power is turned on.





EX39-based lamps will work in both E39 and EX39 sockets.





PHYSICAL CHARACTERISTICS





LAMP DIMENSIONS

| A (Illuminated Length) | 5.83" | | |
|-------------------------|--------|--|--|
| B (Body Length) | 10.70" | | |
| C (Diameter) | 3.43" | | |
| BASE TYPE: EX39 (Mogul) | | | |

ORDERING INFORMATION

| ORDER CODE | PACKAGING STYLE | PACK QTY. | ITEM STATUS |
|---------------------------|---------------------------------------|-----------|-------------|
| KT-LED54HID-EX39-850-D-DP | Distributor Pack (Individual Cartons) | 16 | Quick Ship |

CATALOG NUMBER BREAKDOWN



Keystone Technologies • 1390 Welsh Road, North Wales, PA 19454 • Phone (800) 464-2680 • Fax (888) 966-0556 • www.keystonelamp.com